

Features:

- High Attenuation Range 0.25dB to 31.75dB
- Low Insertion Loss
- Step error less than ± 0.1 dB
- High Linearity
- Long Battery Life
- Economical
- Small & Rigid design



Description:

The RFATV107-608-30X is a battery operated Digital Step Attenuator which operates from 100 MHz to 5.8 GHz frequency range. It provides -0.25 to -31.75dB attenuation with different step size. The signal output uses an SMA female connector to facilitate the connection to RF test equipment. Its laboratory quality specifications will meet most engineering laboratory requirements. The same features that make the model RFATV107-608-30X a good choice for an engineering Lab.

Applications:

- Microwave radio & very small aperture terminals (VSATs)
- Cellular infrastructure
- Test equipment & sensors
- IF & RF designs

Standard Accessories:

- USB Charger (5V / 2A) (Figure. 1)
- SMA(M) to SMA(M) 50 Ohms cable 10" (Figure. 2)




Figure 1




Figure 2

Electrical Specifications:

Frequency Range:	100 MHz to 5.8 GHz
Attenuation Range :	-0.25 dB to -31.75 dB (± 2.45 dB)
Step Size (X)(dB) :	0.25(A) / 0.5(B) / 1.0 (C) / 3.0 (D) / 10.0 (E)
In / Out Impedance:	50 Ohm
Input Power:	+20dBm (Max) / 0 VDC (Max)
Insertion Loss :	
0.1GHz – 1GHz :	-1.5 dB (Typ.)
1 GHz – 2GHz :	-1.6 dB (Typ.)
2 GHz – 4GHz :	-2.5 dB (Typ.)
4 GHz – 5.8GHz :	-4.25 dB (Typ.)
Return Loss :	≥ -10 dB
OLED Display :	27.0 X 11.5 mm (128 X 32)
Operating temperature:	0 °C to 50 °C
Battery Operation :	8 Hour for single charge
Input / Output Connector:	SMA (F)
Input Supply:	5V/2A
Power Consumption:	0.49 Watt (Max.)

Mechanical Specifications:

Dimension (mm) :	L = 103 L' = 32.7 B = 114.7 B' = 38 H = 25	
Shape:	T shape	
Weight:	430gm	

